

3/PRTS

10/529737
JC17 Rec'd PCT/PTO 30 MAR 2005

COMMUNICATION SYSTEM

Communication system with network nodes for operating industrial machines, and method for controlling a communication system

The invention relates to a communication system with network nodes as generically defined by the preamble to claim 1 and to a method for controlling a communication system as generically defined by the preamble to claim 10.

In the most various areas of technology, communication systems with network nodes of a control and/or drive network are used for operating industrial machines. A communication system with network nodes, in a first embodiment, connects a plurality of network nodes over a closed signal path to form a network. Data and control signals are passed through all the network nodes over the ringlike signal path. One network node is embodied for instance as a control unit. In a master/slave configuration, one control unit is provided that performs a master function and controls the other control units, which perform slave functions. For instance, a control signal is output by the master control unit via an output into the signal path and is received again via an input from the closed signal path.

To assure reliable signal information, it is for instance known, along with a primary ring as the signal path, to dispose a further signal path as a secondary ring. The secondary ring is embodied parallel to the primary ring and represents a redundant data line. If one of the two signal paths fails, then the other, intact signal path takes on the task of exchanging the data between the control units.

1 The object of the invention is attained by the
2 communication system having the characteristics of claim 1
3 and the method for controlling a communication system as
4 defined by the characteristics of claim 10.

5
6 One advantage of the invention is that the
7 communication system has a plurality of networks, which can
8 be configured flexibly. In this way, the network structure
9 can be adapted to malfunctions of the network nodes or of the
10 control units connected to the network nodes. The
11 configuration can furthermore be adapted to various machine
12 conditions as well. Depending on the particular application
13 it may be advantageous to incorporate a network node into a
14 first or a second network. For instance, control units that
15 fail relatively often can be into small networks or
16 incorporated into networks upon whose failure either a
17 malfunction is rapidly detected or only a slight impairment
18 of the entire communication system results. Thus the
19 communication system as defined by claim 1 offers increased
20 flexibility in the distribution of the various networks,
21 which furthermore have signal paths that are independent of
22 one another. Because of the independence of the signal paths,
23 if one network fails, the capability of the other networks to
24 function is advantageously unimpaired.

25
26 In a simple embodiment of a communication system, two
27 networks can each be connected to one another via a
28 bidirectional signal path, and the bidirectional signal path
29 can be embodied between two network nodes of the different
30 networks. In this way, a simple, economical connection of the
31 two networks can be established. Depending on the embodiment,
32 the bidirectional signal path is represented for instance by
33 two electric lines.

1 Preferably, the communication system of the invention
2 is used in printing machines, especially printing machines
3 that have a plurality of printing units. Depending on the
4 embodiment, the control units of one printing unit may be
5 incorporated in a network, or the control units of all the
6 printing units of one printing machine may be incorporated in
7 a network.

8
9 The communication system of the invention furthermore
10 offers the advantage that the function of the control units
11 of the networks can be varied as a function of the
12 distribution of the control units among the various networks.
13 For instance, in a first configuration of the networks, one
14 control unit can perform a master function, and in a second
15 configuration of the networks it can perform a slave
16 function. Correspondingly, the slave function of a control
17 unit can be changed to a master function. Preferably, each
18 network has one control unit with a master function.

19
20 The invention is described in further detail below in
21 conjunction with the drawings. Shown are

22
23 Fig. 1, a communication system with two networks;

24
25 Fig. 2, a communication system with a modified
26 configuration of the two networks;

27
28 Fig. 3, a communication system for controlling a
29 machine system;

30
31 Fig. 4, a communication system for a printing machine;
32 and

33
34 Fig. 5, part of a communication system for a rotary

1 printing machine.

2

3 Fig. 1 shows a communication system with network nodes
4 1, 2, 3, 4, 5. The communication system is divided up into
5 two networks 11, 12. The first network 11 includes the first,
6 second and third network nodes 1, 2, 3. The second network 12
7 includes the fourth and fifth network nodes 4, 5. Each
8 network node has one switchover unit 8.

9

10 The master control unit bindingly specifies control
11 commands and a time-slot pattern for the slave control units.

12

13 The second network 12 has the fourth and fifth network
14 nodes 4, 5. The fourth and fifth network nodes are connected
15 to one another via two lines 9. The two lines 9 represent a
16 bidirectional signal path 10. The bidirectional signal path
17 10 has one signal course for each transmission direction. For
18 each signal course, one line 9 is used.

19

20 The lines 9 of the first and second networks 11, 12
21 each communicate with switchover units 8 of the network nodes
22 1, 2, 3, 4, 5. A switchover unit 8 of a network node 1, 2, 3,
23 4, 5 has the functionality that, as a function of the
24 switching position of the switchover unit 8, the switchover
25 unit 8 connects the lines 9 of a network node 1 through 5
26 with one another, and these lines carry signals in one
27 direction through the network node 1, 2, 3, 4, 5. In Fig. 1,
28 the line 9, which delivers signals from the first network
29 node 1 to the second network node 2 at the input RX,
30 communicates via the switchover unit 8 of the second network
31 node 2 with the line 9 that carries signals from the second
32 network node 2 to the third network node 3 via the output TX.
33 Correspondingly, the switchover unit 8 of the second network
34 node 3 connects the line 9, which delivers signals from the

1 third network node 3 to the second network node 2, to the
2 line 9, which carries signals from the second network node 2
3 to the first network node 1.

4
5 In a second switching position, the switchover unit 8
6 interrupts the communication of the lines 9 that carry the
7 signals in one direction through the network node 1, 2, 3, 4,
8 5 and connects the lines 9 of a signal path 10, by way of
9 which lines signals are exchanged between two network nodes,
10 to one another.

11
12 Depending on the application, preferably at least the
13 master control unit is connected to a data bus, by way of
14 which configuration commands from outside for configuring the
15 networks 11, 12 are delivered. Since the switching position
16 of the switchover unit 8 is variably adjustable, the
17 configuration of the communication system can be adjusted
18 flexibly. This offers the advantage that defects in one line
19 9, for instance, of a network 11, 12 are excluded. For
20 instance, one of the lines 9, which is embodied between the
21 third and fourth network nodes 3, 4, could be defective. This
22 defect has an influence on the capability of the first and
23 second networks 11, 12 to function, since the first and
24 second networks 11, 12 do not communicate with one another
25 over the two lines 9 that are embodied between the third and
26 fourth network nodes 3, 4. The first and second networks 11,
27 12 each have their own ringlike, closed signal course. In the
28 second network 12, the control unit of the fourth network
29 node 4 forms the master control unit, and the control unit of
30 the fifth network node 5 forms the slave control unit.

31
32 A further advantage of the flexible embodiment of the
33 differing size of the networks 11, 12 is that the network
34 nodes 1 through 5 can be connected to one another in a

1 different distribution to make various networks.

2

3 In a simple embodiment, all five network nodes 1, 2, 3,
4 4, 5 could form a single network. All that is required for
5 this is to switch over the switchover unit 8 of the third and
6 fourth network nodes 3, 4 accordingly. The number of networks
7 and network nodes is not limited to the numbers in the
8 exemplary embodiment but instead can be selected to suit the
9 particular application.

10

11 In the embodiment shown in Fig. 3, the control unit of
12 the first network node 1 takes on the master functionality,
13 which specifies a leading axis for the second and third
14 network nodes 2, 3. The first, second and third network nodes
15 are realized by a first, second and third control unit,
16 respectively.

17

18 The control unit of the first network node 1 takes on
19 the control of the drive mechanisms 13 that are provided for
20 controlling a printing unit 15 of a printing machine. The
21 control unit of the second network node 2 controls the drive
22 mechanisms 13, connected to the second network node 2, that
23 are associated with a painting unit 16. The control unit of
24 the third network node 3 controls the drive mechanisms 13
25 that are associated with a stamping unit 17.

26

27 The flexible configuration of the communication system
28 of the invention offers the advantage that depending on the
29 makeup of a processing complex and its subsidiary units,
30 networks of different sizes can be formed. For instance,
31 functions that are of lesser importance for the mode of
32 operation of the processing complex may be controlled in a
33 dedicated network. Functions that are especially critical for
34 a correct mode of operation of the processing complex are

1 likewise handled in a dedicated network. There is furthermore
2 the possibility, for instance in the embodiment of Fig. 3, if
3 the stamping unit 17 fails, to interrupt the signal path 10
4 between the second and third network nodes, yet printing and
5 painting of a printed item is still possible. Hence failure
6 of the stamping unit 17 does not cause a complete failure of
7 the processing complex of the communication system. A failure
8 of the stamping 17 is recognized for instance by the master
9 control unit of the first network node 1, which performs a
10 corresponding monitoring of the slave control units of the
11 second and third network nodes 2, 3.

12
13 The first and second networks 11, 12 each have one
14 master control unit. If the master control unit of the first
15 or of the second network 11, 12 fails, for instance, and the
16 other control units of the network 11, 12 are incapable of
17 taking on the master function, then an interconnection of the
18 first and second networks 11, 12 may be effected. The master
19 control unit that is still functioning then takes on the
20 master function for the first and second networks 11, 12.
21 Thus in this application as well, the embodiment of a
22 communication system with a plurality of networks which can
23 be configured flexibly has substantial advantages.

24
25 Fig. 5 shows a different embodiment of the
26 communication system of the invention. In Fig. 5, part of a
27 rotary printing machine with two folding machines is shown
28 schematically. Fig. 5 shows part of a first ring line 6,
29 which is connected to five network nodes 1, 2, 3, 4, 5. The
30 first ring line 6 has two parallel lines 9. In this exemplary
31 embodiment, a network node 1 through 5 has an interface 22
32 and a control unit 23. The interface 22 serves the purpose of
33 data exchange between the ring line 6, which has two lines 9,
34 and the control unit 23. The control unit 23 serves to

1 control drive mechanisms 13. The control unit 23 is connected
2 to the interface 22 via a data connection. In the exemplary
3 embodiment shown, the interface 22 simultaneously takes on
4 the function of the switchover unit 8. The interface 22 is
5 controlled by the control unit 23. The functionality of the
6 switchover unit 8 is preferably implemented via software
7 programs. The control unit 23 is connected to drive
8 mechanisms 13 of a first printing tower 24. The control unit
9 23 of the second network node 2 is connected to drive
10 mechanisms 13 of a folding machine. The control unit 23 of
11 the third network node 3 is connected to drive mechanisms 13
12 of a second printing tower 26.

13

14 The further ring lines 14 for instance represent a
15 Synax control group produced by Indramat. The drive
16 mechanisms 13 preferably have an electronic gear
17 functionality, which enables shaftless synchronization of the
18 drive mechanisms 13. Each control unit of a network node
19 preferably calculates its own leading axis, which is defined
20 as a function of the leading axis of the master control unit,
21 and which is followed by the drive mechanisms 13 that are
22 triggered by the control unit. The use of a master control
23 unit offers the advantage that the master control unit can be
24 embodied in an especially fail-safe way and is for instance
25 securely supplied with voltage. A failure of the master
26 functionality is thus avoided. Hence a shutoff of the
27 communication system and hence of the triggered machine is
28 assured without damaging the machine, even if there is a
29 defect in one of the further control units. The first and
30 second ring lines 6, 7 preferably represent a closed optical
31 waveguide ring.

32

33 Because of the flexible distribution of the networks, a
34 control unit that is defective or must be switched off can

1 for instance be removed from the other networks. Thus the
2 other networks continue to be functional even though one
3 control unit has been switched off. Hence shutting off one
4 control unit does not impair the capability of the other
5 control units to function.